

**DECK HARNESS CONNECTORS for h36**

All connectors to be male pins with female connectors.

3/2/2007

<b>CONN. F</b>	<b>WIRE# (DECK)</b>	<b>NOTES:</b>	<b>CONN. TYPE</b>
1	#1, 16ga blue, CABIN LIGHTS		Deutsch - DT Series - 12 pin
2			
3	#5, 14ga gray/red, ANCHOR LIGHT		
4	#6, 14ga gray/green, STEAMING LIGHT		
5	#13, 16ga blue, CABIN LIGHTS		
6			
7			
8	#11, 16ga blue, STBD LIGHTS		
9	#15, 16ga gray/yellow, STERN LIGHT		
10	#19, 16ga blue/white, ARCH LIGHT		
11	#25, 16ga gray/white, BOW LIGHT		
12	#16, 14ga red/black, GPS		

<b>CONN. SS</b>	<b>WIRE# (TO STEREO)</b>		<b>CONN. TYPE</b>
1	#9, 16ga white/orange, PORT MAIN SPEAKER (+)		Deutsch - DT Series - 8 pin
2	#10, 16ga white/yellow, PORT MAIN SPEAKER (-)		
3	#21, 16ga white/pink, PORT ARCH SPEAKER (+)		
4	#22, 16ga white/yellow, PORT ARCH SPEAKER (-)		
5	#23, 16ga white/gray, STBD ARCH SPEAKER (+)		
6	#24, 16ga white/black, STBD ARCH SPEAKER (-)		
7	#30, 16ga white/blue, STBD MAIN SPEAKER (+)		
8	#31, 16ga white/black, STBD MAIN SPEAKER (-)		

<b>CONN. Arch</b>	<b>WIRE# (TO ARCH)</b>		<b>CONN. TYPE</b>
1	#19, 16ga blue/white, ARCH LIGHT		Deutsch - DT Series - 6 pin
2	#20, 16ga yellow, ARCH LIGHT (-)		
3	#21, 16ga white/pink, PORT ARCH SPEAKER (+)		
4	#22, 16ga white/yellow, PORT ARCH SPEAKER (-)		
5	#23, 16ga white/gray, STBD ARCH SPEAKER (+)		
6	#24, 16ga white/black, STBD ARCH SPEAKER (-)		